

Hey!

I'm WatchY4

Let's get started

Many more languages here!



Do you want a video tutorial?



SIM card is my friend



Insert an active nano SIM card into the SIM card slot. If you have a SIM card in your WatchY4 box, you can use that SIM card, or you can use any of your own.

Some SIM cards may have a PIN code. If you don't want to enter the PIN code manually into the watch, insert the SIM card into your phone and disable the PIN in the settings.

Credit and data are my oxygen



We need to make sure that the inserted SIM card contains enough credit and data. Without credit, I can't make calls, and without data, I can't pinpoint my location, interact with the app.

Download the app from the provider of the SIM card inserted in the WatchY4, add the number of this SIM card to the app, and occasionally check how much credit and data is left on the SIM card.

Download the LAMAX Connect app



LAMAX Connect is our official app for connecting with me and your little explorer. Through the app, you can conveniently communicate with us, track our location and we can even video call each other.

The app is available for both Android and iPhone. Just scan the QR code to download.

I need to connect to the app



Bind me with the LAMAX Connect app on your mobile phone. You can pair me using the QR code, which you can generate in my menu under the **"Bind"** tab. In case your phone can't scan the QR code from the watch, manually enter the code under the QR code into the LAMAX Connect app.

Don't forget to name the watch. In the first step, you enter the parent's name, and in the second step, the child's name. You can test the correct connection by sending a nice message through the chat in the app.

Add my mobile number in the app



In the LAMAX Connect app, click on **“More”**
-> **“Device name”** -> **“Watch phone number”** and add
the mobile number here, including the +420 or 00420
prefix for the Czech Republic or another country.

Save important contacts



In the LAMAX Connect app, you can add important contacts that automatically sync with me so your little explorer can easily call them. In the app you can also set up call blocking from numbers that are not stored in me.

Contacts can also have the "Emergency call" function. This feature allows you to quickly call an SOS contact in an emergency by simply holding down the side button for five seconds.

To add contacts, click on **"More"** -> **"Contacts in the watch"** -> Tap on the "+" icon in the upper right corner.

Home is safe



You can add safety zones in the LAMAX Connect app. As soon as your little explorer enters the designated zone, you'll get a notification. The same applies if they leave the safe zone.

To add safety zones in the app tap on **"More"** tab -> **"Safety zone"**.

One zone can be home and another zone can be school, for example.

Turn on automatic location detection



Together with the LAMAX Connect app, I can automatically record the location of your little explorer, so there's no need to manually check the location. If you want me to stay charged as long as possible, update my location manually through the app, as automatic location updates affect my battery life.

At the end of the day, you can look at the location history of where your child has been exploring the world.

Set this in the LAMAX Connect app under the **"Location tab"** -> **"three dots"** -> **"Location mode."**

Correct time is important



The correct time is automatically detected via the inserted SIM card.

Sometimes it's good to check that the server hasn't changed my time zone.

You can find the time settings in the LAMAX Connect app
-> **"More"** -> **"Device setting"**.

Check the QR code and discover
many more useful features!

